

Yield Reporting Form: HP LaserJet Enterprise M806 cartridge model CF325X

Declared ISO yield

Toner cartridge yield:Average cartridge yield 34,500 standard pages¹*Declared yield value in accordance with ISO/IEC 19752 based on continuous printing*Calculated test values

| | |
|---|--------|
| Average ¹ | 36,127 |
| Standard Dev. | 1,410 |
| 90% lower confidence limit ¹ | 35,634 |

| | |
|---|---|
| Test date: beginning | 8/8/2013 |
| Test dates: ending | 8/29/2013 |
| Number of cartridges used in testing | 24 |
| Number of cartridges used in calculations | 24 |
| Type of cartridge | Hewlett Packard CF325X all in one |
| Shake procedure used? | No |
| Print mode | Continuous |
| Job size | 500 pages per job |
| Number of engines used in testing | 4 |
| Media | HP Multipurpose |
| Paper size | Letter |
| Paper feed orientation | Long edge |
| Computer model | vSphere Client virtual PC |
| Operating system | Microsoft Windows 7 Enterprise with SP1 |
| Application software | Public domain file transfer utility |
| Print driver version | None: Internal PDF interpreter |
| Connection type | network |
| Test page version* | Version 4.0 pdf |

| | |
|------------------------|----|
| Power on/off every day | No |
|------------------------|----|

| Engine serial numbers: | Engine Firmware Version: |
|------------------------|--------------------------|
| JP1CF6B0B1 | 2301087_394639 |
| JP1CF6B0B4 | 2301087_394639 |
| JP1CF6B08K | 2301087_394639 |
| JP1CF6B09J | 2301087_394639 |

*filename: Download_Free___19752_Test_Chart__.pdf from ISO SC28 website

Cartridge testing data

| | | |
|----------------------------|--------------------|-----------------|
| Test environmental limits: | Temperature | Humidity |
| | °C | %RH |
| Max running average | 25.2 | 51 |
| Min running average | 22.7 | 46 |
| Average | 23.0 | 50 |

| CF325X | | LJ Enterprise M806 | |
|------------------|-----------------|---------------------------|------------------------|
| Cartridge | Lot Code | Engine SerNo | Cartridge Yield |
| CF325X-001 | 3F18Z1a | JP1CF6B0B1 | 36892 |
| CF325X-002 | 3F25Z1a | JP1CF6B0B4 | 36108 |
| CF325X-003 | 3G15Z1a | JP1CF6B08K | 36056 |
| CF325X-004 | 3F18Z1a | JP1CF6B09J | 34178 |
| CF325X-005 | 3F25Z1a | JP1CF6B0B1 | 35863 |
| CF325X-006 | 3G15Z1a | JP1CF6B0B4 | 36572 |
| CF325X-007 | 3F18Z1a | JP1CF6B08K | 35332 |
| CF325X-008 | 3F25Z1a | JP1CF6B09J | 39352 |
| CF325X-009 | 3G15Z1a | JP1CF6B0B1 | 35822 |
| CF325X-010 | 3F18Z1a | JP1CF6B0B4 | 35896 |
| CF325X-011 | 3F25Z1a | JP1CF6B08K | 35482 |
| CF325X-012 | 3G15Z1a | JP1CF6B09J | 37191 |
| CF325X-013 | 3F18Z1a | JP1CF6B0B1 | 38135 |
| CF325X-014 | 3F25Z1a | JP1CF6B0B4 | 35917 |
| CF325X-015 | 3G15Z1a | JP1CF6B08K | 35720 |
| CF325X-016 | 3F18Z1a | JP1CF6B09J | 34310 |
| CF325X-017 | 3F25Z1a | JP1CF6B0B1 | 37864 |
| CF325X-018 | 3G15Z1a | JP1CF6B0B4 | 35986 |
| CF325X-019 | 3F18Z1a | JP1CF6B08K | 33641 |
| CF325X-020 | 3F25Z1a | JP1CF6B09J | 36640 |
| CF325X-021 | 3G15Z1a | JP1CF6B0B1 | 37344 |
| CF325X-022 | 3F18Z1a | JP1CF6B0B4 | 33428 |
| CF325X-023 | 3F25Z1a | JP1CF6B08K | 35664 |
| CF325X-024 | 3G15Z1a | JP1CF6B09J | 37655 |

¹ In an ISO report two values are commonly listed: declared ISO yield and calculated test values. Generally, the calculated test values are higher than the declared ISO yield. Actual cartridge yields vary considerably based on content of images printed and other factors. For more information visit www.hp.com/go/learnaboutsupplies.